

Reactel, Incorporated

Reacting First to All Your Filter Needs.

700 MHz LTE Fullband Bandpass Filter

16CX11-752-X108N11

Reactel is proud to present this bandpass filter as another member of the growing family of 700 MHz LTE units. This particular unit is suitable for the entire 700 MHz band and is centered at 752 MHz. Reactel has a large variety of 700 MHz LTE and other wireless band filters and multiplexers; please contact the factory with your specifications.



Specifications

Center Frequency	752 MHz
Passband	698 – 806 MHz, minimum
Insertion Loss	≤ 1.2 dB @ Passband
Attenuation	≥ 18 dB @ DC – 695 MHz ≥ 30 dB @ 824 – 896 MHz
Return Loss	≥ 10 dB @ Passband
Connectors	Type N Female in / out
Size	4.5" high x 2.9" wide x 13.1" long, nominal excluding connectors